


Mounting and
Operating Instructions

Home station hands-free feature
1280 ..

GIRA

Device description

The Home station hands-free feature is part of the Gira door communication system and consists of the following components:




- 1 Door communication bus coupler
- 2 Audio connection cable
- 3 Speech insert
- 4 Cover frame
(not included in scope of supply)
- 5 Loudspeaker top unit
- 6 Operating buttons
for home station hands-free feature



Attention

Installation and mounting of electrical devices may only be carried out by a qualified electrician.

The Home station hands-free feature is installed in two common flush-mounted panel boxes:



1. Connect the door communication bus coupler to the 2-wire bus at the BUS terminals and, if necessary, the lines of the level call button to the "ET" terminals.
2. Insert the audio connection cable into one of the two System connectors of the bus coupler.
3. Guide the audio connection cable to the upper flush-mounted panel box and install the bus coupler in the lower flush-mounted panel box.
4. Insert the audio connection cable into one of the two System connectors of the speech insert.
5. Install the speech insert.
6. Set the cover frame in place and attach the operating buttons and loud-speaker top unit to the flush-mounted inserts.


Start-up

Once you have installed all of the devices (door and home stations, control unit etc.), you can start up the door communication system.

Start-up is described in the system manual included with the control unit.

Operation

Operating buttons



The following functions are executed with the operating buttons:

Accepting a call

If an incoming call is present, the  LED flashes for 2 minutes.



Briefly press the  button to start intercom communication with the person at the outdoor station. The  LED illuminates continuously during the intercom communication.



Maximum conversation time

The maximum conversation time is 2 minutes. When this time expires, the conversation is automatically interrupted.

Enforcement function

If the background noises at the outdoor station are so loud that automatic switching of the speech direction is not guaranteed, you can activate the enforcement function.



For this purpose, press and hold the  button while speaking. While the button is being pressed, only the person at the Home station can speak and be heard. To release the voice control to the door station, release the  button again.

Ending the call



To end the voice connection, briefly press the  button.

The  LED switches off.


Opening the door



Press the  button.

If several doors are present, the door opener whose door station made the door call is operated within 2 minutes. It switches to the main door 2 minutes after the start of the call or 30 seconds after the door call is ended.

Switching light on/off (only in conjunction with a switching actuator)



Press the  button to switch the light (e.g. the outdoor or staircase illumination) on.

Setting the speech volume

The speech volume is changed to one of five levels during intercom communication.



Press "+" to increase the speech volume.



Press "-" to decrease the speech volume.

Setting the call tone volume

The call tone volume is changed to one of five levels when no intercom communication is in effect.



Press "+" to increase the call tone volume.




Press "-" to decrease the call tone volume.

Deactivating/activating the call tone



Press the  button to deactivate the call tone.

The  LED illuminates continuously if the call tone is deactivated.



Press the  button again to reactivate the call tone.

The  LED switches off.



Only deactivate the call tone if necessary

Deactivate the call tone in special cases only. Otherwise, the danger is present that you will not hear the ringing in an emergency, for example.

Setting call tone melody

The Comfort home station offers five call tone melodies, which can be individually assigned to the call buttons of the door station, the internal call buttons of other home stations or the floor call button.

This allows, for example, a different door station call button with an individual call tone melody to be assigned in a household with several people (e.g. parents, children).

The call tone melody is set as follows:



1. Trigger the call tone whose melody you would like to change by pressing the corresponding call button which was previously taught in.



2. To change the melody of the last triggered call tone, press and hold the  button on the home station and **simultaneously** press



- the "+" button to select the melody that follows or



- the "-" button to select the previous melody.



- ✓ Each time the buttons "-" and "+" are pressed, a new call tone melody is set.



Note

When deleting the call button assignment to the home station, the corresponding call tone melodies are reset to the factory setting.

Automatic door opener

The automatic door opener is, e. g., used in doctor's offices when approx. 4 s after pressing a door-station call button, the door opener is to be automatically operated. If several door stations are present in the system, the automatic function acts on the door opener of the door station from which the door call was triggered.



Function not active in factory setting

To use the automatic door opener, this function must be activated during commissioning. Details are contained in the system manual.

Switching on automatic door opener

3 s



1. Simultaneously press the buttons  and  for approx. 3 seconds to switch on the automatic door opener.
- ✓ When the automatic door opener is switched on, the LED  lights up continuously. The door opener is automatically operated after a door call.

Switching off automatic door opener

3 s



1. Simultaneously press the buttons  and  for approx. 3 seconds to switch off the automatic door opener.
- ✓ The  LED goes out.



Behaviour after power failure

Following a power failure the automatic door opener is switched off.

Acceptance of guarantee

The warranty is provided in accordance with statutory requirements via the specialist trade.

Please submit or send faulty devices postage paid together with an error description to your responsible salesperson (specialist trade/installation company/electrical specialist trade).

They will forward the devices to the Gira Service Center.

Gira
Giersiepen GmbH & Co. KG
Elektro-Installations-
Systeme
Postfach 1220
42461 Radevormwald
Deutschland
Tel +49 (0) 21 95 / 602 - 0
Fax +49 (0) 21 95 / 602 - 191
www.gira.de
info@gira.de

10 41 03 73 19/11

GIRA